

# ADDRESSABLE BEAM SMOKE DETECTOR

## Features

- ▶ 7 - 70 m standard detection range
- ▶ Extensions kits available to enhance detection range up to 160 m
- ▶ Approved by VdS to EN 54-12:2015
- ▶ Continually corrects itself against building movement
- ▶ Brand new optics design reduces false alarms
- ▶ Fully compatible with the Hochiki ESP analogue addressable protocol.

## Description

The ESP FIREbeam Xtra is a Reflective Beam Smoke Detector fully approved to EN 54-12:2015 which can offer a maximum detection range of 160 m. The unit's newly designed optics increase sensitivity whilst the enhanced internal software reduces false alarms.

The detector comes with a separate controller unit which allows engineers to commission, monitor and maintain from ground level. Detection range is 70 m for the standard unit, increasing to 140 m or 160 m with the addition of the medium or long-range reflector kits.



The detector also features advanced motorised technology allowing it to self-align to the centre of the reflector during commissioning. Once commissioned the detector continually monitors alignment and will automatically realign itself back to the centre of the reflector if any building movement occurs.

The ESP FIREbeam Xtra features an integral loop module allowing full connectivity to the Hochiki ESP analogue addressable loop.

Specification	
Ordering Codes	ESP Firebeam Xtra including controller and 1 reflector covers distance 7-70 m 70KIT140 - Firebeam Xtra Range extension kit 70-140 m 140KIT160 - Firebeam Xtra Range extension kit 140-160 m
Supply Voltage	17 to 41 VDC
Supply Current	3.5 mA (constant current) in all operational states
Constant Current	17 mA (constant current) in fast commissioning
Operating Temperature Range	- 10 °C to + 55 °C
Operating Humidity	10 to 95% RH Non-condensing
Ingress Protection Rating	IP65 (when suitably mounted and terminated)
Optical Wavelength	870 nm
Maximum Angular Alignment	±5°
Maximum Angular Misalignment	Beam Head ±0.4 ° Reflector ±2 ° (static not auto-aligning)
Alarm Sensitivity Levels	25% (1.25 dB) to 50% (3 dB) in 1% (0.05 dB) increments (default 35% (1.87 dB))
Weight (g) / Dimensions (mm)	Beam Head 1.1 / H 180 x W 155 x D 137 Controller 0.55 / H 185 x W 120 x D 62
FIREbeam Xtra Ancillaries	ADAPTER FIREbeam Xtra head interface adapter to mount to unistrut REP-CONT FIREbeam Xtra replacement controller REFLECTOR FIREbeam Xtra single reflector COND-KIT FIREbeam Xtra anti-condensation window for head and single anti-condensation reflector  REF-AC FIREbeam Xtra single anti-condensation reflector WINDOW-AC FIREbeam Xtra anti-condensation window 70KIT140-AC FIREbeam Xtra anti-condensation range extension kit 70 - 140 metres 140KIT160-AC FIREbeam Xtra anti-condensation range extension kit 140 - 160 metres FB-BRACKET FIREbeam Xtra adjustable wall bracket for FIREbeam or single reflector SHORT RM FIREbeam Xtra short range mask for up to 20 metres



For further information visit our website. Hochiki reserves the right to alter the specification of its products from time to time without notice. Although every effort has been made to ensure the accuracy of the information contained in this document it is not warranted or represented by Hochiki to be a complete and up-to-date description. Check online for current version.

