

Case C (260)

Casing for an Ajax module and a 7 Ah battery



3
GRADE
EN 50131

PD 6662
2017

INCERT

Safe and quick connection

Install LineSupply (45 W) Fibra or LineSupply (75 W) Fibra with 7 A·h battery using Case. Run cables and secure the device in the simplest way. Quick and reliable fastening using durable latches and non-falling screws.



This is a casing with slots for LineSupply (45 W) Fibra, LineSupply (75 W) Fibra, and 7 A·h battery. There are alternative-sized casings available for different device combinations.



Easy installation and maintenance

- Pre-installed tamper to detect the lid opening and alert of detachment of the casing from the surface
- Mounting holes placed at different angles and pre-installed spirit level to set the casing horizontally
- Perforated zones and fasteners for easy cable routing and management
- Multiple use – even after dismantling and changing device configuration
- All mountings are included – PRO does not need to take an additional mount to the facility

Compliance	Compatibility	Installation	Technical specifications	Complete set
EN 50131 (Grade 3) PD 6662:2017 INCERT	Compatible devices LineSupply (45 W) Fibra LineSupply (75 W) Fibra 7 A·h battery (not included in the set)	Operating temperature range from -10°C to +40°C Operating humidity up to 75%	Color white, black Dimensions 260 × 210 × 93 mm Weight 716 g	Case C (260) Installation kit Quick start guide



For detailed information, scan the QR code or follow the link:
ajax.systems/support/devices/case-fibra/

-  support@ajax.systems
-  @AjaxSystemsSupport_Bot
-  ajax.systems